


This Is An Original Product From Fulham Co., Inc

Description : WorkHorse Series Versatile, Solid State Electronic Ballast. Small Case Size, High Power Factor, High Frequency, Light Weight, Also Available In 120/230/277V 50/60 Hz.

This Ballast Will Operate Following Lamps.

REFER TO LAMP WATTS/TYPE

INPUT VOLT: 120V ± 10%, 50/60Hz LAMP WATTS/TYPE **T5CR40W CR32W** 22+32 CR F24T5 F54T5 CFTR42W F15T8 F15T8 LAMPS OPERATED 1 2 3 INPUT WATTS 28 40 36 28 25 56 42 36 LINE CURRENT: 0.33 0.25 0.32 0.23 0.50 0.37 0.25 0.35 POWER FACTOR 0.93 0.93 0.93 0.92 0.94 0.93 0.92 0.93 BALLAST FACTOR 0.79 0.89 0.69 0.93 0.92 0.83 0.91 0.89 EFFICACY FACTOR 2.16 3.20 1.94 3.70 1.64 2.00 3.28 2.25 THD 38% 39% 37% 41% 34% 38% 39% 36% **EMI/RFI COMPLIANCE** FCC PART 18-A (Non-Consumer) "A" SOUND RATING BALLAST TYPE **INSTANT START** VOLTAGE TRANSIENTS ANSI 62.41 INPUT/PROTECTION FUSE -30 °C (-20 °F) MIN. OPERATING TEMP 70 ⁰C (158 ⁰F) MAX. CASE TEMP **ENERGY STAR 4.0** APPROVALS/CLASS UL LISTED, CLASS " P ", 1 OR 2 OUTDOOR



Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of <u>5 years</u> from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use. For additional warranty guide line, please refer to our Complete Product Catalog OR <u>call Customer Service at 1-323-599-5000</u>. DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED.

DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED. Address: 12705 South Van Ness Ave., Hawthorne, CA 90250 Tel.: 1-323-599-5000, Fax.: 1-323-754-9060. Website: www.fulham.com 2006-20SP-1 rev N

ELECTRICAL DATA




This Is An Original Product From Fulham Co., Inc

Description : WorkHorse Series Versatile, Solid State Electronic Ballast. Small Case Size, High Power Factor, High Frequency, Light Weight, Also Available In 120/230/277V 50/60 Hz.

This Ballast Will Operate Following Lamps.

REFER TO LAMP WATTS/TYPE

INPUT VOLT: 120V ± 10%, 50/60Hz LAMP WATTS/TYPE FT24W **FT36W** FT40W T5CR55W CFQ26W F32T8 F60T8HO CFQ26W LAMPS OPERATED 1 2 1 1 2 **INPUT WATTS** 24 31 41 53 45 38 61 47 LINE CURRENT: 0.22 0.28 0.37 0.47 0.93 0.34 0.54 0.42 0.93 POWER FACTOR 0.91 0.92 0.93 0.93 0.93 0.94 0.94 **BALLAST FACTOR** 0.81 0.90 0.85 0.91 0.86 1.18 1.10 0.87 EFFICACY FACTOR 2.18 1.88 3.75 2.65 1.62 3.10 1.80 1.85 THD 41% 40% 37% 36% 30% 36% 34% 36% EMI/RFI COMPLIANCE FCC PART 18-A (Non-Consumer) " A " SOUND RATING **BALLAST TYPE INSTANT START** ANSI 62.41 VOLTAGE TRANSIENTS INPUT/PROTECTION FUSE -30 ⁰C (-20 ⁰ F) MIN. OPERATING TEMP 70 °C (158 ° F MAX. CASE TEMP **ENERGY STAR 4.0** APPROVALS/CLASS UL LISTED, CLASS " P ", 1 OR 2 OUTDOOR



Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of <u>5 years</u> from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use. For additional warranty guide line, please refer to our Complete Product Catalog OR <u>call Customer Service at 1-323-599-5000</u>. DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED.

DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED. Address: 12705 South Van Ness Ave., Hawthorne, CA 90250 Tel.: 1-323-599-5000, Fax.: 1-323-754-9060. Website: www.fulham.com 2006-20SP-2 rev N

ELECTRICAL DATA



This Is An Original Product From Fulham Co., Inc


Description : WorkHorse Series Versatile, Solid State Electronic Ballast. Small Case Size, High Power Factor, High Frequency, Light Weight, Also Available In 120/230/277V 50/60 Hz.

This Ballast Will Operate Following Lamps.

REFER TO LAMP WATTS/TYPE

ELECTRICAL DATA

INPUT VOLT: 120V ± 10%, 50/60Hz										
LAMP WATTS/TYPE	F17T8	F17T8	F32T8	F32T8	CR40WT9	F24T5HO	F42T6	F72T8HO		
LAMPS OPERATED	2	1	1	2	1	2	2	1		
INPUT WATTS	33	21	38	61	36	40	61	73		
LINE CURRENT:	0.30	0.19	0.34	0.54	0.32	0.36	0.54	0.65		
POWER FACTOR	0.93	0.92	0.93	0.94	0.93	0.94	0.94	0.94		
BALLAST FACTOR	1.02	1.22	1.18	0.96	0.94	0.80	0.92	1.05		
EFFICACY FACTOR	3.08	5.81	3.10	1.58	2.60	2.00	1.51	1.43		
THD	37%	40%	36%	33%	37%	36%	33%	32%		
EMI/RFI COMPLIANCE	FCC PART 18-A (Non-Consumer)									
SOUND RATING	"A"									
BALLAST TYPE	INSTANT START									
VOLTAGE TRANSIENTS	ANSI 62.41									
INPUT/PROTECTION	FUSE									
MIN. OPERATING TEMP	-30 ⁰ C (-20 ⁰ F)									
MAX. CASE TEMP	70 ⁰ C (158 ⁰ F)									
ENERGY STAR 4.0	-									
APPROVALS/CLASS	UL LISTED, CLASS " P ", 1 OR 2 OUTDOOR									



Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of <u>5 years</u> from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use. For additional warranty guide line, please refer to our Complete Product Catalog OR <u>call Customer Service at 1-323-599-5000</u>. DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED.

DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED. Address: 12705 South Van Ness Ave., Hawthorne, CA 90250 Tel.: 1-323-599-5000, Fax.: 1-323-754-9060. Website: www.fulham.com 2006-20SP-3 rev N



This Is An Original Product From Fulham Co., Inc


Description : WorkHorse Series Versatile, Solid State Electronic Ballast. Small Case Size, High Power Factor, High Frequency, Light Weight, Also Available In 120/230/277V 50/60 Hz.

This Ballast Will Operate Following Lamps.

REFER TO LAMP WATTS/TYPE

ELECTRICAL DATA

INPUT VOLT: 120V ± 10%, 50/60Hz									
LAMP WATTS/TYPE	F39T5HO	F20T12	F15T8						
LAMPS OPERATED	1	2	1						
INPUT WATTS	38	30	18						
LINE CURRENT:	0.34	0.27	0.16						
POWER FACTOR	0.93	0.93	0.91						
BALLAST FACTOR	0.84	0.94	1.16						
EFFICACY FACTOR	2.20	3.14	6.27						
THD	37%	38%	42%						
EMI/RFI COMPLIANCE	FCC PART 18-A (Non-Consumer)								
SOUND RATING	"A"								
BALLAST TYPE	INSTANT START								
VOLTAGE TRANSIENTS	ANSI 62.41								
INPUT/PROTECTION	FUSE								
MIN. OPERATING TEMP	-30 ⁰ C (-20 ⁰ F)								
MAX. CASE TEMP	70 ⁰ C (158 ⁰ F)								
ENERGY STAR 4.0					-				
APPROVALS/CLASS	UL LISTED, CLASS " P ", 1 OR 2 OUTDOOR								



Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of <u>5 years</u> from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use. For additional warranty guide line, please refer to our Complete Product Catalog OR <u>call Customer Service at 1-323-599-5000</u>. DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED.

DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM Co., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED. Address: 12705 South Van Ness Ave., Hawthorne, CA 90250 Tel.: 1-323-599-5000, Fax.: 1-323-754-9060. Website: www.fulham.com 2006-20SP-4 rev N